


Ver: 1.0

HelloBaby®

User Manual

2.4GHz Digital Wireless Video Baby Monitor
2.4GHz Digital Wireless Video Baby Camera



Model: HB6256

The pictures are for reference only, please subject to practicality.

www.hellobaby.net.cn
service@hellobaby.net.cn

Thank you for purchasing the HB6256 Baby Monitor. With our baby monitor, you could see and hear your baby sleeping or playing in their room anytime.

Please return your original dated sales receipt for your records. For warranty service of your product, you will need to provide a copy of your dated sales receipt to confirm warranty status. Registration is not required for warranty coverage.

Please make sure the following included in your package

Parent unit x 1 Camera unit x 1 Wall-mounting kit x 1 Power Adapter x 2 User manual x 1

1. SAFETY INSTRUCTIONS
CAUTION: Keep the device away from children.
Strangulation Hazard: Children have STRANGLED in cords. Keep this cord out of the reach of children (more than 3ft (0.9m) away). Never use extension cords with AC Adapters. Only use the AC Adapters provided.
Choking Hazard: This product contains small parts, please be careful when unpack and assemble the product.
Read and keep to instructions: All the safety and operating in instructions should be read before the video baby monitor is operated. This product cannot replace responsible adult supervision.
Water and moisture: This product is designed for indoor use only. The unit should not be exposed to rain, moisture, dripping or splashing. No objects filled with liquid should be placed on top of, or beside the product, such as a glass or vase. This item should not be used near water.
DO NOT: use the appliance if the cord or plug is damaged. If your baby monitor is not operating properly or has suffered any damage, contact "service@hellobaby.net.cn" service center to request inspection and repair of the appliance in order to avoid any possible risk.
DO NOT: do not attempt to repair or adjust any of the electrical or mechanical functions of the unit. Otherwise, the guarantee will be voided.
Warning: This baby monitor should not be used on a bed, sofa, rug or similar surface that may block the ventilation openings, or be placed in an enclosed area such as a bookcase or drawer that may impede air flow.
Keep away from sources of heat: This unit should not be exposed to direct heat sources such as candle, radiator, heat register, stove or other appliance that emits heat. This unit should not be left in direct sunlight.
Power source: This unit should only be used with the AC power adapters included in this package (rated 5V DC 1A).
Damage requiring service: This unit should be serviced by qualified personnel only when: Objects have fallen or liquid has been spilled into the product.
- The units have been exposed to rain;

- The units do not appear to operate normally or exhibits a distinct change in performance; - The units have been dropped or the enclosure damaged;

2. WARRANTY TERMS
We offer one-year warranty from the original purchase date against defects in workmanship and materials. If you have warranty or support issues, please contact our after-sales service via email.

3. INSTALLATION GUIDELINES

* To use your parent unit and camera unit together, you have to establish a radio link between them, and the range will be affected by environmental conditions.
* The units have been dropped or the enclosure damaged;
* Any large metal object, like a refrigerator, a mirror, a filling cabinet, metallic doors or reinforced concrete between the baby and parent unit may block the radio signal.
* The signal strength may also be reduced by other solid structures, like walls, or by radio or electrical equipment, such as TV, computers, cordless or mobile phones, fluorescent lights or dimmer switches.
* Use of other 2.4GHz product, such as wireless networks (Wi-Fi routers), Bluetooth systems, or microwave ovens, may cause interference with this product, so keep the baby monitor away at least 3ft (1.5m) from such products, or turn them off if they cause interference.

4. PLACEMENT OF THE BABY MONITOR
The camera can be placed on the ceiling or mounted on the wall. Don't place baby monitor on soft quilts or blankets or in the corners of cupboards, shelves, etc. Keep the baby monitor away from heat sources such as radiators, chimneys, cookers and direct sunlight; Keep the baby unit away from TV sets, microwave oven and radios. If interference occurs, move the camera to elsewhere.
* Place the camera within 6 feet (2 meters) of the area being monitored for optimum performance.

5. GETTING STARTED

5.1 TURN ON THE BABY UNIT:
1. Insert the DC plug of the power adapter into the DC jack in the rear of the Baby Unit;
2. Insert the other end of the power adapter into suitable electrical outlet;
3. Once the adapter is connected, the power LED will light up.


5.2 TURN ON THE PARENT UNIT:
1. Insert the DC plug of the power adapter into the DC Jack in the side of the parent Unit;
2. Insert the other end of the power adapter into a suitable electrical outlet;
3. Press and hold the power key 3 seconds on the side of the parent unit;
4. Once parent unit is on, the power LED will light up and the image will display on the LCD

5.3 INFRARED NIGHT VISION (AUTOMATIC)
The infrared night vision function allows the camera to pick up images in dark or low light conditions. In this mode, only black and white images will be displayed on the monitor. The optimum image is where baby unit is 6ft (2m) away from object. The camera is in night vision mode, the icon will be displayed on the top of the screen.

6. PRODUCT OVERVIEW

6.1 ICONS OVERVIEW:


6.2 PARENT UNIT OVERVIEW:



Sound Level Indicator
Zoom / Scan
Left/Two-Way Talk
Menu/OK
Up Key
Right Key
Down Key
Volume/Brightness
Charging LED/Power LED
MIC
Left Key

Antenna
Power Key
Stand
DC Jack
Speaker
Reset Key

6.3 BABY UNIT OVERVIEW:



MIC
Light sensor
Infrared LEDs
Lens
Antenna
Power LED
DC-Jack
Pair key
Temperature sensor

7. KEY OPERATION

7.1 TURN ON/OFF
Press and hold the power key for 3 seconds to turn on/off the parents unit.
Press once to tilt the camera up by one step. Press and hold to tilt continuously.
Press once to tilt the camera down by one step. Press and hold to tilt continuously.

7.2 UP & KEY
Press once to pan the camera left by one step. Press and hold to pan continuously.

7.3 RIGHT & KEY
Press once to pan the camera right by one step. Press and hold to pan continuously.

7.4 DIGITAL ZOOM
Press and hold to view /scan camera during scan mode, the scan icon will be displayed on the top of screen. Each camera's view will be displayed on the LCD around 10 seconds then change to next camera.

7.5 DIGITAL ZOOM
Press and hold key around 2 seconds to operate zoom in/out.

7.6 Two-Way Talk
Press and hold key enter two way talk mode. A microphone icon will be displayed in the corner of the LCD screen. Release the key to stop.
Note: When you are in the two-way talk mode, the parent unit speaker is muted.

8. MENU OPERATION

8.1 PARENT THE CAMERA AND TWO-WAY TALK
The baby unit is pre-registered to your parent unit. You do not need to register it again unless the baby unit loses its link with the parent unit. To re-register your baby unit, or register a

WARNING

Strangulation Hazard: Children have STRANGLED in cords. Keep this cord out of the reach of children (more than 3 ft (0.9 m) away). Do not remove this tag.

AVERTISSEMENT

DANGER D'ÉTRANGLEMENT: Des enfants se sont ÉTRANGLÉS avec des cordons électriques. Gardez le cordon/étiquette hors de la portée des enfants (à plus de 0.9m/3 pi du lit d'enfant). Ne pas enlever cette étiquette.

Risk Group 1
WARNING if emitted from this product. Do not stare at operating lamp
Product tested against EN62471

FC CE UKA BC

Made in China

new baby unit, follow the procedure below:

Note: Camera icon with means it is well registered. You should select and pair with the camera icon without sign.

8.1.1 ADD CAMERA

1. Press the MENU key then the menu will pop up;
2. Press the key until the camera icon is selected by red box;
3. Press key to enter into sub-menu, then press key to select your desired camera;
4. Press key enter into sub-menu, Press key to select then press key;
5. When the icon is displayed on the LCD screen, press the PAIR key on the back of camera;
7. If fails, repeat the above steps.

8.1.2 DELETE CAMERA

1. Press the MENU key and the menu will pop up;
2. Press the key until the camera icon is selected by red box;
3. Press key to enter into sub-menu, then press key to select the camera you want to delete;
4. Press key enter into sub-menu, Press key to select then press key;
5. Press key to select icon to delete the camera;
6. Press key to confirm.

8.2 VOLUME

1. Press the MENU key then the menu will pop up;
2. Press the key until the volume icon is selected by red box;
3. Press the key enter into sub-menu, then press key to select the camera you want to adjust;
4. Press key to select the desired volume level from level 1 ~ 5.

8.3 DISPLAY BRIGHTNESS

1. Press the MENU key then the menu will pop up;
2. Press the key until the brightness icon is selected by red box;
3. Press key enter into sub-menu;
4. Press key to select the desired brightness level from level 1 ~ 5.
(The default brightness level setting is level 3).

8.4 TEMPERATURE UNIT SETTING

1. Press the MENU key then the menu will pop up;
2. Press the key until the temperature icon is selected by red box;
3. Press key enter into sub-menu;
4. Press key to select the "F" or "C" for setting temperature unit;
5. Press key to confirm;
6. Press key to Exit.

Note: The detected temperature range is 0°-40 °C.

8.4.1 TEMPERATURE ALARM SETTING

1. Press the key to select for turning on alarm function; Press key to confirm;
2. Press the key to select for turning off alarm function; Press key to confirm.

8.4.2 SET TEMPERATURE H/LO ALERT LIMITS

1. Press key to select for H/Lo limits settings;
2. Press the key until the lullaby icon is selected by red box;
3. Press key to adjust the lo limit when (green) is selected;
4. Press key to confirm.

Note: The high temperature alarm default setting is 36 °C, and the low temperature alarm default setting is 8 °C, when the temperature goes above or below the settings, the temperature icon will display on the screen. Will alert user by beeps. Press any key on the parent unit to stop beeping and flashing.

8.4.3 LULLABY SETTING

You can soothe the baby by playing a gentle lullaby from the Camera unit.

1. Press the MENU key and the menu will pop up;
2. Press the key until the lullaby icon is selected by red box;
3. Press key enter into sub-menu;
4. Press key to select one of the available lullabies, you can pick single playback, loop all (all) or playback PC or stop key to confirm.
5. Press key to confirm.

Note: The lullaby default setting is OFF.

8.4.4 ALARM SETTING

1. Press the MENU key and the menu will pop up;
2. Press the key until the alarm icon is selected by red box;
3. Press the key enter into sub-menu, Press the key to select the alarm time you need;
4. Press key to confirm.
5. Press key to confirm.

Note: The minimum unit is 0.5 hour. The maximum setting is 5 hours (2 levels).
Note: Once the alarm is turned on, alarm icon will display on the screen.
Note: If the alarm is ringing, press any key on the parent unit to turn the alarm off.
Note: If you don't turn off the alarm, the alarm will ring for 1 minute. After three minutes the alarm will ring again to continue. The alarm will ring for three times in total, if there is no sound around the baby unit within 30 seconds, it will stop audio transmission and turn off the

screen of the parent unit. When the baby unit detects any sounds louder than the sensitivity level, it will start transmitting the signal to the parent unit again and turn on the screen of the parent unit. To change the ECO level, please follow the below instructions.

1. Press the MENU key and the menu will pop up;
2. Press the key until the ECO icon is selected by red box;
3. Press key enter into sub-menu, then press key to select desired level;
4. Press key to confirm.

8.5 LANGUAGE SETTING

Note: Low sensitivity level, the baby have to make a lot of sound before the ECO function will be activate;
Note: Middle sensitivity level;
Note: High sensitivity level, the baby don't have to make a lot of sound before the ECO function will be activate;

1. Press the MENU key and the menu will pop up;
2. Press the key until the language icon is selected by red box;
3. Press key enter into sub-menu, then press key to select the language you need;
4. Press key to confirm;
5. Press key to Exit.

9. TECHNICAL DATA

Frequency	2412MHz~2469MHz
Parent Unit: Input: 100-240VAC 50/60Hz Output: 5V DC 1A	
Power Adaptor Camera Unit: Input: 100-240VAC 50/60Hz Output: 5V DC 1A	
Operating Range	Up to 1000ft (300m) outdoor (line of sight) Up to 165ft (50m) indoor
Display	5.0" Diagonal TFT LCD
Batter (parent Unit)	Li-ion 3.7V 4000mAh (4.8Wh)
Battery Life	Up to 12 hours
Mainm power	<150mW
Operation Temperature	+32°F~+104°F (0°C~40°C)
Battery Charging Temperature	+50°F~+104°F (10°C~40°C)
Operation environment	Relative Humidity: 15%~85%

10. TROUBLE SHOOTING

No reception on the monitor

- * The power adapters may not be properly connected;
- * Confirm that the camera and monitor are ON;
- * Camera may be far away from the monitor;
- * Camera and monitor may not be properly paired; follow PAIRING instructions;
- * There may be interference from other wireless devices;
- * The camera or monitor may be placed too close to many metal objects;
- * Other electronic devices may be interfering with the signal;
- * The battery power may be too low;

Interference or poor reception

- * Move the monitor away from the camera;
- * Other electronic devices may be interfering with the signal;
- * The battery power may be too low;

Audio feedback (High pitched noise / frozen picture noise)

- * The camera and monitor may be placed too close;
- * The volume on the camera may be set too high;

11. MAINTENANCE

1. Clean your baby monitor with a slightly damp or anti-static cloth.
* Never use cleaning agents or solvents.
* Do not attempt to repair or adjust any of the electrical or mechanical functions of the unit.
* Remember to dispose of the product in an environmentally responsible way.
* For proper collection and processing of these products, take them to the collection points designated by local authorities. You can also contact the store where you purchased the product.
* Improper or incorrect use of batteries may cause corrosion or battery leakage, which could cause personal injury or damage to property. Use only the types of the batteries which are indicated in this manual.
CAUTION: Risk of Fire and Burns. Do Not Open, Crush, Heat Above 45 Degree C or Incinerate. Follow Manufacturer's Instructions.

- Disposal of a battery into fire or a hot oven, or mechanically crushing or cutting of a battery, that can result in an explosion;
- Leaving a battery in an extremely high temperature surrounding environment can be result in an explosion or the leakage of flammable liquid or gas;
- A battery subjected to extremely low air pressure that may result in an explosion or the leakage of flammable liquid or gas.
- The battery shall not be exposed to excessive heat such as sunshine, fire or the like;

FCC & ISM Statement

This device complies with Part 15 of the FCC Rules and with Industry Canada licence-exempt RSS (standard). Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Cet appareil conforme à la partie 15 des règles de l'IC et aux normes RSS exemptées de licence d'industrie Canada. Le fonctionnement est soumis aux deux conditions suivantes: (1) Cet appareil ne doit pas causer d'interférences nuisibles, et (2) l'appareil doit accepter toute interférence reçue, y compris les interférences pouvant entraîner un fonctionnement défectueux. Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: -- Reorient or relocate the receiving antenna. -- Increase the separation between the equipment and receiver. -- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. -- Consult the dealer or an experienced radio/TV technician for help. This device meets the exemption from the routine evaluation limits in section 2.5 of RSS 102 and compliance with RSS 100 RF exposure, users can obtain Canadian information on RF exposure and compliance. If exemption does not apply, evaluation courante dans la section 2.5 de RSS 102 et conformité avec RSS 100 d'exposition aux RF, les utilisateurs peuvent obtenir des données canadiennes sur l'exposition aux champs RF à la conformité. Cet équipement conforme aux limites d'exposition aux champs RF pour un environnement résidentiel. Cet équipement génère, utilise et émet de l'énergie radiofréquence et, s'il n'est installé et utilisé en conformité avec les instructions, peut causer des interférences nuisibles à la réception radio ou de télévision. Cependant, il n'y a aucune garantie que les interférences ne se produiront pas dans une installation particulière. Si cet équipement provoque des interférences nuisibles à la réception radio ou de télévision, ce qui peut être déterminé en éteignant l'équipement et en le rallumant, l'utilisateur est encouragé d'essayer de corriger l'interférence par l'une ou plusieurs des mesures suivantes: -- Réorienter ou réinstaller l'antenne. -- Augmenter la distance entre l'équipement et le récepteur. -- Brancher l'équipement sur une prise d'alimentation différente de celle à laquelle le récepteur est branché. -- Consulter le revendeur ou un technicien expérimenté en radio/TV pour obtenir de l'aide. Cet équipement est conforme aux limites d'exposition aux rayonnements du Canada établies pour un environnement résidentiel. Cet équipement génère, utilise et émet de l'énergie radiofréquence et, s'il n'est installé et utilisé en conformité avec les instructions, peut causer des interférences nuisibles à la réception radio ou de télévision. Cependant, il n'y a aucune garantie que les interférences ne se produiront pas dans une installation particulière. Si cet équipement provoque des interférences nuisibles à la réception radio ou de télévision, ce qui peut être déterminé en éteignant l'équipement et en le rallumant, l'utilisateur est encouragé d'essayer de corriger l'interférence par l'une ou plusieurs des mesures suivantes: -- Réorienter ou réinstaller l'antenne. -- Augmenter la distance entre l'équipement et le récepteur. -- Brancher l'équipement sur une prise d'alimentation différente de celle à laquelle le récepteur est branché. -- Consulter le revendeur ou un technicien expérimenté en radio/TV pour obtenir de l'aide. Cet équipement est conforme aux limites d'exposition aux rayonnements du Canada établies pour un environnement résidentiel. Cet équipement génère, utilise et émet de l'énergie radiofréquence et, s'il n'est installé et utilisé en conformité avec les instructions, peut causer des interférences nuisibles à la réception radio ou de télévision. Cependant, il n'y a aucune garantie que les interférences ne se produiront pas dans une installation particulière. Si cet équipement provoque des interférences nuisibles à la réception radio ou de télévision, ce qui peut être déterminé en éteignant l'équipement et en le rallumant, l'utilisateur est encouragé d'essayer de corriger l'interférence par l'une ou plusieurs des mesures suivantes: -- Réorienter ou réinstaller l'antenne. -- Augmenter la distance entre l'équipement et le récepteur. -- Brancher l'équipement sur une prise d'alimentation différente de celle à laquelle le récepteur est branché. -- Consulter le revendeur ou un technicien expérimenté en radio/TV pour obtenir de l'aide.

guidelines are based on standards that were developed by independent scientific organizations through periodic and thorough evaluation of scientific studies. The standards include a substantial safety margin designed to assure the safety of all persons regardless of age or health. ISED & FCC RF Exposure Information and Statement the SAR limit of Canada (ISED & FCC) is 1.6 W/kg averaged over one gram of tissue. Device type: Monitor has also been tested against this SAR limit. This device was tested for typical body worn operation with the back of the Monitor kept 0.9m from the body. To maintain compliance with ISED RF exposure requirements, use accessories that maintain an 0.9m separation distance between the user's body and the back of the Monitor. The use of hair clips, holsters and similar accessories should not contain metallic items in its assembly. The use of accessories that do not satisfy these requirements may not comply with ISED RF exposure requirements, and should be avoided. Informations sur le débit d'absorption spécifique (DAS): Cette Montreur répond aux exigences du gouvernement au matière d'exposition aux ondes radio. Les lignes directrices sont basées sur des normes élaborées par des organisations scientifiques indépendantes à travers une évaluation périodique et approfondie des études scientifiques. Les normes comprennent une marge de sécurité substantielle conçue pour assurer la sécurité de toutes les personnes, quelle que soit leur âge ou leur état de santé. Information et déclaration d'ISED sur l'exposition aux RF la limite DAS du Canada (ISED) est de 1,6 W/kg en moyenne sur un gramme de tissu. Type d'appareil: La Montreur a également été testée par rapport à cette limite SAR. Cet appareil a été testé pour des opérations typiques portées sur le corps avec le dos de la Montreur gardé à 9 cm du corps. Pour maintenir la conformité avec les exigences d'exposition RF d'ISED, utilisez des accessoires qui maintiennent une distance de séparation de 9 cm entre le corps de l'utilisateur et l'arrière de la Montreur. L'utilisation de clips de ceinture, d'étoiles et d'accessoires similaires ne doit pas contenir de composants métalliques dans son assemblage. L'utilisation d'accessoires qui ne satisfont pas à ces exigences peut ne pas être conforme aux exigences d'exposition aux RF d'ISED et doit être évitée.

EU Declaration of Conformity (DOC)
Hereby, I declare that the radio equipment type is in compliance with RED Directive 2014/53/EU.
The full text of the EU declaration of conformity is available on the website: www.hellobaby.net.cn

Model: HB6256
Model: Authorized Party(UK): Startline LLC
Address: 24 Hazelwood Drive, Jericho, NY 11753 Tel: 1-516-681-3129
Authorized UK Representative(UK): APFEX EC SPECIALISTS LIMITED
Address: 89 Princess Street, York, YO1 1PE, UK. Info@apex-ec.com
Shenzhen Videmates Technology Co., Ltd
Room 2108, Building 11, Tianan Wangzhuo Phase II, Ganggou Community, Bantian Street, Lianjiang District, Shenzhen, Guangdong, China