

HB6233 英语说明书 (Hellobaby)

说明书为折叠式
尺寸: 540*120MM
材质: 100g双胶纸 (彩色)
版本: V1.0
类型: 环保

版本	修改内容	日期
Ver: 1.0	文件首发。	2022/02/21

设计	审核	审批
王勇		
2022/02/21		


540.00 mm

HelloBaby®

Ver: 1.0

User Manual

2.4GHz Digital Wireless Video Baby Monitor



Model: HB6233

The pictures are for reference only, please submit to practically.

www.hellobaby.net.cn
service@hellobaby.net.cn

Thank you for purchasing the HB6233 Baby Monitor. With your baby monitor, you could see and hear your baby sleeping or playing in their room anytime.

Please retain your original dated sales receipt for your records. For warranty service of your product, you will need to provide a copy of your dated sales receipt to confirm warranty status. Registration is not required for warranty coverage.

PLEASE MAKE SURE THE FOLLOWING INCLUDED IN YOUR PACKAGE

- Parent unit x 1
- Camera unit x 1
- Power Adapter x 2
- Wall-mounting kit x 1

1. SAFETY INSTRUCTIONS

CAUTION: Keep the device away from children.

Strangulation Hazard: Children have STRANGLED in cords. Keep this cord out of the reach of children (more than 3ft (0.9m) away). NEVER use extension cords with AC Adapters. Only use the AC Adapters provided.

Choking hazard: This product contains small parts, please be careful when unpack and assemble the product.

Read and keep to instructions: All the safety and operating instructions should be read before the video baby monitor is operated. This product cannot replace responsible adult supervision.

Water and moisture: This product is designed for indoor use only. The unit should not be exposed to rain, moisture, dripping or splashing. No objects filled with liquid should be placed on top of, or beside the product, such as glass or vase. This item should not be used near water.

DO NOT: Use the appliance if the cord or plug is damaged. If your baby monitor is not operating properly or has suffered any damage, contact "Videolines" service center to request inspection and repair of the appliance in order to avoid any possible risk.

DO NOT: Do not attempt to repair or adjust any of the electrical or mechanical functions of the unit. Otherwise, the guarantee will be made void.

Ventilation: This baby monitor should not be used in a bed, sofa, rug or similar surface that may block the ventilation openings, or be placed in an enclosed area such as a backpack or drawer that may impede air flow.

Keep away from sources of heat: This unit should not be exposed to direct heat sources such as a candle, radiator, heat register, stove or other appliance that emits heat. The unit should not be left in direct sunlight.

Power Source: This unit should only be used with the AC power adapters included in this package (Parent Unit: DC 1A, Camera Unit: DC 1A).

Afterpowering service: This unit should be serviced by qualified personnel only when: Objects have fallen or liquid has been spilled into the product; The units have been exposed to rain.

The units do not appear to operate normally or exhibits a distinct change in performance; The units have been dropped or the enclosure damaged;

2. WARRANTY TERMS
We offer a warranty from the original purchase date against defects in workmanship and materials. If you have warranty or support issues, please contact our after-sales service via email.

3. INSTALLATION GUIDELINES
To use your parent unit and camera unit together, you have to establish a radio link between them, and the range will be affected by environmental conditions.

* Any large metal object, like a refrigerator, a mirror, a filing cabinet, metallic doors or reinforced concrete between the baby and parent unit may block the radio signal.

* The signal strength may also be reduced by other solid structures, like walls, or by radio or electrical equipment, such as TV, computers, radios or mobile phones, fluorescent lights or dimmer switches.

* Use of other 2.4GHz product, such as wireless network (Wi-Fi routers), Bluetooth systems, or microwave ovens, may cause interference with this product, so keep the baby monitor away at least 5ft (1.5m) from such products, or turn them off if they cause interference.

4. PLACEMENT OF THE BABY MONITOR
The camera can be placed on the desktop or mounted on the wall. Don't place baby monitor on soft quilted blankets or in the corners of cupboards, shelves, etc. Keep the baby monitor away from heat sources such as radiators, chimneys, cookers and direct sunlight. Keep the baby unit away from TV sets, microwave ovens and radios. If interference occurs, move the camera to elsewhere;

* Place the camera within 6 feet (2 meters) of the area being monitored for optimum performance.

5. GETTING STARTED

5.1 TURN ON THE BABY UNIT:
1. Insert the DC plug of the power adapter into the DC Jack in the rear of the Baby Unit;
2. Insert the other end of the power adapter into a suitable electrical outlet;

3. Once the adapter is connected, the power LED will light up;

5.2 TURN ON THE PARENT UNIT:
1. Insert the DC plug of the power adapter into the DC Jack in the side of the parent unit;
2. Insert the other end of the power adapter into a suitable electrical outlet;


3. Press and hold the power key 3 seconds on the top of the parent unit;
4. Once parent unit is on, the power LED will light up and the image will display on the LCD

5.3 INFRARED NIGHT VISION (AUTOMATIC)
The infrared night vision function allows the camera to pick up images in dark or low light conditions. In this mode, only black and white images will be displayed on the monitor, the optimum image in the white baby unit is ETV (2m) away from object. The camera is in night vision mode, the icon will be displayed on the top of screen.


6. PRODUCT OVERVIEW



6.2 PARENT UNIT OVERVIEW:



6.3 BABY UNIT OVERVIEW:



7. KEY OPERATION

7.1 POWER SAVE / SCREEN OFF
Short press the power key to turn on / off the screen.

7.2 UP & KEY
Press once to tilt the camera up by one step. Press and hold to tilt continuously.

7.3 DOWN & KEY
Press once to tilt the camera down by one step. Press and hold to tilt continuously.

7.4 LEFT & KEY
Press once to pan the camera left by one step. Press and hold to pan continuously.

7.5 RIGHT & KEY
Press once to pan the camera right by one step. Press and hold to pan continuously.

7.6 CAMERA VIEW / SCAN
Press scan key to view / scan camera; during scan mode, the scan icon will be displayed on the top of screen. Each camera view will stay on the LCD around 10 seconds (then change to next camera).

7.7 DIGITAL ZOOM
Press and hold to zoom key around 2 seconds to operate zoom in / out;

7.8 TWO-WAY TALK
Press and hold to talk key to enter two way talk mode. A microphone icon will be displayed on the top of the LCD screen. Release the key to stop.

Note: When you are in the two-way talk mode, the parent unit speaker is muted.

8. MENU OPERATION

8.1 PANNING THE CAMERA AND PARENT UNITS
The baby unit is pre-registered to your parent unit. You do not need to register it again unless the baby unit loses its link with the parent unit. To re-register your baby unit, or register a new baby unit, follow the procedure below:

WARNING
Strangulation Hazard: Children have STRANGLED in cords. Keep this cord out of the reach of children (more than 3 ft (0.9 m) away). Do not remove this tag.

AVERTISSEMENT
DANGER D'ÉTRANGLEMENT: Des enfants se sont ÉTRANGLÉS avec des cordons électriques. Gardez le cordon électrique hors de la portée des enfants (à plus de 0.9m/3 pi du lit d'enfant). Ne pas enlever cette étiquette.



Made in China

Note: Camera icon with "" means it is well registered. You should select and pair with the camera icon without "" sign.

8.1.1 ADD CAMERA
1. Press the MENU key then the menu will pop up;
2. Press the key or key until the camera icon is highlighted; then press key or key to select your desired camera;

3. Press OK key to enter into sub-menu;
4. Press key or key to select ADD CAMERA; then press OK key;
5. When the icon is displayed on the LCD screen, press the PAIR button on the back of camera;

6. Once paired, appears on the LCD screen.
7. If fails, repeat the above steps.

8.1.2 DELETE CAMERA
1. Press the MENU key and the menu will pop up;
2. Press the key or key until the camera icon is highlighted; then press key or key to select your desired camera;

3. Press OK key to enter into sub-menu;
4. Press key or key to select DEL CAMERA; then press OK key;
5. Press key to select; deletes the camera;

6. Press OK key to confirm the option.

8.3 VOLUME
1. Press the key and the menu bar will pop up;
2. Press the key or key until is highlighted;
3. Press the key or key to select the desired volume level from level 1 ~ 5.
(The default volume level setting is level 2 and level is OFF).

8.3 TEMPERATURE UNIT SETTING
1. Press the key and the menu bar will pop up;
2. Press the key or key until the temperature icon is highlighted;
3. Press key or key to select between "F" or "C";
4. Press OK key to confirm;

5. Press the key to exit.

8.3.1 SET TEMPERATURE ALERT LIMITS
8.3.1.1 TEMPERATURE RANGE IS 0~50 °C
8.3.1.1 TEMPERATURE ALARM SETTING
1. Press key or key to select; then for alarm setting;
2. Press key or key followed by for confirming alarm on then followed by for switching off alarm function;

8.3.1.2 SET TEMPERATURE VOX ALERT LIMITS
1. When is highlighted at alarm setting then press to enter H/L limits settings.
2. Press key or key to adjust the H/L limit then press to confirm.
3. Press key or key to adjust the VOX level, please follow the below instructions.

4. Press key or key to select the VOX sensitivity level.
5. Press key to confirm setting.

4. Press key or key to adjust the Lo limit then press to confirm.
5. Press key or key to select the Hi limit then press to confirm.
Note: The high temperature alarm range is 20~40 °C, and the low temperature alarm range is 0~19 °C. The high temperature alarm default setting is 36 °C, and the low temperature alarm default setting is 8 °C. When the temperature goes above or below the settings, the temperature icon turns red. It will flash to alert user by audio beep. Press any key on the parent unit to stop beeping and flashing.

8.5 LULLABY SETTING
You can soothe the baby to sleep playing a gentle lullaby from the Camera unit.

1. Press the MENU key and the menu will pop up;
2. Press the key or key until the lullaby icon is highlighted;
3. Press key or key to select one of the 8 available lullabies; you can pick single playback, loop (all lullabies playback) or stop;

4. Press OK key to confirm.
Note: The lullaby default setting is OFF.

8.5.1 ALARM SETTING
You use the Parent Unit to set an alarm as a reminder for you to take care of your baby if an alarm time is selected, the Parent Unit will beep at the end of the selected hour period from 30min to 60s with 30min step interval. The alarm will sound for about 1 minute when the time is reached, or can be stopped by pressing any key;

1. Press the MENU key and the menu will pop up;
2. Press the key or key until the alarm icon is highlighted;
3. Press the key or key to select the expected times;

4. Press OK key to confirm.
Note: The alarm default setting is OFF. When the alarm is ringing, press any key on the parent unit to stop.

8.5.2 DISPLAY BRIGHTNESS
1. Press the key and the menu bar will pop up;
2. Press the key or key until the brightness icon is highlighted;
3. Press key or key to select the desired brightness level from level 1 ~ 5.
4. Press OK key to confirm the setting (level 3).

8.7 VOX SETTING
This mode allows you to control the sound activation of your baby unit. If there is no sound around the baby unit within 30 seconds, it will stop audio transmission and turn off the screen of the parent unit. When the baby unit detects any sounds louder than the sensitivity level, it will start transmitting the signal to the parent unit again and turn on the screen of the parent unit.

1. Press key or key to select the VOX level, please follow the below instructions.
2. Press key or key until is highlighted;
3. Press key or key to select the VOX sensitivity level.

4. Press key to confirm setting.

Note: Sensitivity levels and indications
8.8 Hear everything from your baby. The speaker of the parent unit is continuously on.
8.9 Hear all sounds from soft babbling. If your baby does not make any sound, the speaker of the parent unit is off.

Note: The speaker of the parent unit only goes on if the baby makes loud sounds (e.g. crying).

9. TECHNICAL DATA

Frequency	2403.5MHz~2423.5MHz
Parent Unit Input	100~240VAC 50/60Hz
Output	5V DC 1A
Camera Unit Input	100~240VAC 50/60Hz
Output	5V DC 1A
Operating Range	Up to 1000ft (300m) outdoor (line of sight) Up to 165ft (50m) indoor
Display	3.2" Display TFT LCD
Battery (Parent Unit)	Li-ion 3.7V 950mAh (3.525Wh)
Battery life	Up to 6 hours
Maximum power	< 1900m
Operation environment	Operating Temperature: +32F/+104F (0°C~40°C) Battery Charging Temperature: +59F/+144F (10°C~40°C) Relative Humidity: 15%~85%

10. TROUBLE SHOOTING

No reception on the monitor

• The power adapter may not be properly connected;
• Confirm that the camera is monitor on DC;
• Camera may be far away from the monitor;
• Camera & monitor may not be properly paired; follow PAIRING instructions.

Interference or poor reception

• Move the monitor closer to the camera;
• The camera and monitor may be placed too close to any metal objects;
• Other electronic devices may be interfering with the signal;
• The battery power may be too low.

Audio feedback (high pitched noise)

• The camera and monitor may be placed too close;
• The volume on the monitor may be set too high;

Frozen Picture on Screen

• Repower the baby unit (plug out the adapter, then plug it into the socket again);
• Press the RESET key at the back of parent unit;

11. MAINTENANCE
• Clean your baby monitor with a slightly damp or anti-static cloth.
• Never use cleaning agents or solvents.

12. DISPOSAL GUIDE FOR BATTERY AND PRODUCT
Do not attempt to repair or adjust any of the electrical or mechanical functions of the unit.

Remember to dispose of the product in an environmentally responsible way:
• For proper collection and processing of these products, take them to the collection points designated by local authorities. You can also contact the store where you purchased the product.

Improper or incorrect use of batteries may cause corrosion or battery leakage, which could cause personal injury or damage to property. Use only the types of batteries which are indicated in this manual.

CAUTION: Risk of Fire and Burns. Do Not Open, Crush, Heat Above 45 degree C or Incinerate. Follow Manufacturer's Instructions.

• Disposal of a battery into fire or a hot oven, or mechanically crushing or cutting of a battery, can result in an explosion;

• Leaving a battery in an extremely high temperature surrounding environment that can result in an explosion or the leakage of flammable liquid or gas;

• A battery subjected to extremely low air pressure that may result in an explosion or the leakage of flammable liquid or gas;

• The battery shall not be exposed to excessive heat such as sunshine, fire or the like;

FCC/CE ISDE Statement
This device complies with Part 15 of the FCC Rules and with Industry Canada licence-exempt RSS (Standard). Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Cet appareil est conforme à la partie 15 des règles de la FCC et aux normes RSS exemptes de licence d'Industrie Canada. Le fonctionnement est soumis aux deux conditions suivantes: (1) l'appareil ne doit pas causer d'interférences nuisibles, et (2) cet appareil doit accepter toute interférence reçue, y compris les interférences pouvant entraîner un fonctionnement indésirable.

Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is

encouraged to try to correct the interference by one or more of the following measures:
• Reorient or relocate the receiving antenna.
• Increase the separation between the equipment and receiver.
• Connect the equipment to an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

This device meets the exemption from the routine evaluation limits in section 2.5 of RSS 102 and compliance with RSS 102. If exposure, users can obtain Canadian information on RF exposure and compliance.

Cet appareil est conforme à l'exemption des limites d'évaluation courantes dans la section 2.5 du cor-102 et conforme aux RSS 102 de l'exposition aux RF. Les utilisateurs peuvent obtenir des données canadiennes sur l'exposition aux champs et, si la conformité.

This equipment complies with the Canada radiation exposure limits set forth for an unpowered environment.
Cet équipement est conforme aux limites d'exposition aux rayonnements du Canada établies pour un environnement non activé.

Radiation Exposure Statement for camera
This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.
Cet équipement doit être installé et utilisé à une distance minimale de 20 cm entre le radiateur et votre corps.

Specific Absorption Rate (SAR) Information:
This Monitor meets the government's requirements for exposure to radio waves. The guidelines are based on standards that were developed by independent scientific organizations through periodic and thorough evaluation of scientific studies. The standards include a substantial safety margin designed to assure the safety of all persons regardless of age or health. IS95-R: Exposure Information and Statement of the SAR limits of Canada (IS95) is 1.6 W/kg averaged over one gram of tissue. Device types: Monitor has also been tested against this SAR limit. This device was tested for typical body-worn operations with the back of the Monitor kept 5cm from the body. To maintain compliance with IS95-RF exposure requirements, use accessories that maintain an 8mm separation distance between the user's body and the device. The use of back clips, holders and similar accessories should not contain metallic components in its assembly. The use of accessories that do not meet these requirements may not comply with IS95-RF exposure requirements, and should be avoided.

Information sur le débit d'absorption spécifique (DAS):
Cet appareil répond aux exigences de puissance en matière d'exposition aux ondes radio. Les lignes directrices sont basées sur des normes établies par des organisations scientifiques indépendantes à travers une évaluation périodique et approfondie des études scientifiques. Les normes comprennent une marge de sécurité substantielle conçue pour assurer la sécurité de toutes les personnes, quel que soit leur âge ou leur état de santé.

Information et déclaration d'IS95 sur l'exposition aux RF à la limite DAS du Canada (IS95) est

de 1,6 W/kg en moyenne sur un gramme de tissu. Types d'appareils: la Montreur a également été testée par rapport à cette limite SAR. Cet appareil a été testé pour des opérations typiques portées sur le corps avec le dos de la Montreur gardé à 5 cm du corps. Pour maintenir la conformité avec les exigences d'exposition RF d'IS95, utilisez des accessoires qui maintiennent une distance de séparation de 8 mm entre le corps de l'utilisateur et l'arrière de la Montreur. L'utilisation de clips de ceinture, d'étuis et d'accessoires similaires ne doit pas contenir de composants métalliques dans son assemblage. L'utilisation d'accessoires qui ne satisfont pas à ces exigences peut ne pas être conforme aux exigences d'exposition aux RF d'IS95 et doit être évitée.

EU Declaration of Conformity (DOC)
Hereby, Videolines declares that the radio equipment type is in compliance with RED Directive 2014/53/EU.
The full text of the EU Declaration of conformity is available on the website: www.hellobaby.net.cn

Model: HB6233
Responsible Party(S): Startline LLC
Addr: 22 Hazelwood Drive, Jericho, NY 11753 Tel: 1-516-681-3729

Authorized UK Representative(UR): Startline weni net
Addr: 12 Progress Road, Eastleigh, Hampshire, UK Tel: +44(0)7405 570 2799

Shenzhen Videolines Technology Co., Ltd.
701, Building 3, No. 1, Zhenhan Road, Ganjing Community, Jihua Street Office, Longgang District, Shenzhen

WARNING IR emitted from this product. Do not stare at operating lamp
Produced against EN62471

Risk Group 1

12

13

14

15

16

17

18

19

20